

TIME SWITCH IROMQRE-12 instruction

Please read the instructions carefully before using, in order to correctly use.
After reading, please safekeeping.

Safety precautions

WARNING

- Do not use the time switch with wrong mistakes in any equipment that causes human death or significant social problems, so please do not use this kind of switch.
- If you want to use the time switch in equipment that could cause a financial loss if a failure occurs (such as in heaters and refrigerators), select a model with excess capacity in terms of characteristics and performance, then also take safety measures such as providing duplicate circuits.

CAUTION

- Do not disassemble or modify the time switch. You may receive an electrical shock, cause a fire, or damage the switch.
- Please do not touch the terminals after the power is on. Otherwise there will be the danger of electric shock.
- If it is found that the terminal part of the rusting, please as soon as possible replacement of good or you may cause a fire by poor contact.
- Do not use the time switch where it might be splashed by water or oil you may receive an electrical shock, cause a fire, or damage the switch.

① Setting the operating time

- Fold the setting pin inside(OFF) or outside(ON) at the desired time you want the action to occur.


Caution

- (1) Do not try to fold the four setting pins next to the current time display(⌚), you can not set these times. If you force it, you may damage the switch.
- (2) If the time you want is in this area, turn the minute in the direction shown by the arrow and then fold the setting pin.

- [Example] This occasion
- The setting like this at 10:00 in the morning [ON] at 10:30 in the morning [OFF].
 - The setting like this 01:00 in the afternoon [ON] and 2:30 in the afternoon [OFF].

CAUTION
Please bring home time set button successively down (outside of dial). Set the button down, be sure to hear "Khaki" the exact sound.

Names of each parts



Contact state



② Adjusting the current time

- Turn the minute dial the direction shown by the arrow to match the current time.

Caution

- (1) Make sure to turn the minute knob only in the direction shown by the arrow. Turning it backward forcibly may damage the switch.
- (2) The dial shows the time using a 24 hour system.
- (3) When adjusting the current time be careful not confuse AM and PM.


Setting the manual switch

- Set the manual switch to the [] position.


- (1) : The output will be turned on and off at the set times.
- (2) : The output will be on, regardless of the settings (continuously ON).
- (3) : The output will be off, regardless of the settings (continuously OFF).
- You can use a manual switch load operation test, and please set to "ON" or "OFF" position.

- CAUTION** Please turn it to [] position after you finished your testing

Dimensions (unit:mm)




Connection



How to install

Front panel installation

Installation type : 68x68mm
Before installing, turn the knob to the level
Install rotary knob to the vertical fixed
The mounting panel is less than 4mm



Re.val.co. International s.r.l. - RVC -

Via G.Di Vittorio 13 – 20017 Rho (MI) - ITALY
www.revalcointernational.it info@revalcointernational.it